

## Recommended Circuit Breaker for Hafco Guillotines

**Disclaimer-** These circuit breaker ratings are a suggestion only and can vary. Consideration must be given to cable size; the type of installation and voltage drop on the particular circuit as determined in AS3008/2017. This can be determined by a qualified electrician.

<b>Guillotines</b>					
<b>Stock code</b>	<b>Model No.</b>	<b>Voltage</b>	<b>Full load current</b>	<b>Circuit breaker</b>	<b>Type of breaker</b>
S934/S	<b>HG-2504</b>	415	9 amp	20 amp	C curve
S937/S	<b>HG-2506</b>	415	15 amp	25 amp	C curve
S940/S	<b>HG-3206</b>	415	15 amp	25 amp	C curve
S946/S	<b>HG-4006</b>	415	20 amp	25 amp	C curve
S942	<b>HG-3212</b>	415	36 amp	40 amp	D curve
S948	<b>HG-4012</b>	415	36 amp	40 amp	D curve
S915	<b>SG-2504E</b>	415	12 amp	20 amp	C curve
S916	<b>SG-2506E</b>	415	15 amp	25 amp	C curve
S918	<b>SG-3206E</b>	415	15 amp	25 amp	C curve
S923	<b>HG-460B</b>	415	9.5 amp	20 amp	C curve
S924A	<b>MG-440</b>	415	10.3 amp	20 amp	C curve
S926A	<b>MG-840</b>	415	9.6 amp	20 amp	C curve
S927	<b>HG-840B</b>	415	9.5 amp	20 amp	C curve
S535	<b>SG-420</b>	240	13.4 amp	20 amp	C curve