

## **Recommended Circuit Breaker for Hafco Guillotines**

**Disclaimer-** These circuit breaker ratings are a suggestion only and can vary. Consideration must be given to cable size; the type of installation and voltage drop on the particular circuit as determined in AS3008/2017. This can be determined by a qualified electrician.

<b>Stock code</b>	<b>Voltage</b>	<b>Full load current</b>	<b>Circuit breaker</b>	<b>Type of breaker</b>
<b>Guillotines</b>				
S934	415	9 amp	20 amp	C curve
S937	415	15 amp	25 amp	C curve
S940	415	15 amp	25 amp	C curve
S946	415	20 amp	25 amp	C curve
S942	415	36 amp	40 amp	D curve
S948	415	36 amp	40 amp	D curve
S915	415	12 amp	20 amp	C curve
S916	415	15 amp	25 amp	C curve
S918	415	15 amp	25 amp	C curve
S923	415	9.5 amp	20 amp	C curve
S924a	415	10.3 amp	20 amp	C curve
S926a	415	9.6 amp	20 amp	C curve
S927	415	9.5 amp	20 amp	C curve
S535	240	13.4 amp	20 amp	C curve
S537	240	13.4 amp	20 amp	C curve